

IN THE UNITED STATES PATENT & TRADEMARK OFFICE

Application for Utility Patent

Title:

---

IMPLICIT ADDRESSING SEQUENTIAL MEDIA DRIVE WITH  
INTERVENING CONVERTER SIMULATING EXPLICIT  
ADDRESSING TO HOST APPLICATIONS

---

Inventor(s):

Robert Beverley Basham  
Leonard George Jesionowski

Atty. Docket: TUC9-2001-0092-US1  
( IBMT-070 )

prepared by-

DAN HUBERT & ASSOC.

3111 CAMINO DEL RIO NORTH  
FOURTH FLOOR  
SAN DIEGO, CA 92108

858.274.9456 VOICE  
858.274.9466 FAX

DANNO@CTS.COM

## BACKGROUND OF THE INVENTION

### 1. Field of the Invention

5 The present invention relates to sequential data storage machines such as magnetic tape drives. More particularly, the invention concerns the modification of an implicit addressing sequential media drive by adding a hardware and/or software converter in order to simulate performance of an explicit addressing sequential media drive from the perspective of host applications.

### 2. Description of the Related Art

10 In the past, small computer system interface (SCSI) tape drives have used "stateless" commands. With stateless commands, also called "implicit addressing" commands, knowledge of current addressing is implied. Stated another way, an implicit Read, Write, or other position command consists of a command to start the operation at the current position without explicitly starting at a particular address. The host application or storage manager issues tape access and positioning commands that are relative. The following is an example of a series of implicit addressing commands: WRITE LENGTH 2, WRITE LENGTH 2, WRITE LENGTH 2. The components of each command include a write instruction and the number of units of data to be written.

15 Accordingly, it is crucial to keep track of the current write location, since the commands only specify a location relative to the last command. Many failures are difficult to recover from since the host application or device driver does not always know exactly where the drive is positioned after a failure. Accordingly, implicit addressing is limited because failed SCSI

commands may leave the host without knowledge of the current tape position. Low level interconnect failures that are passed up to the command layer can result in failed backup jobs with retry of the entire job potentially taking hours, if possible at all. Another potential problem is that commands can be misordered by the time they reach the tape drive, causing the tape drive to apply them incorrectly.

Proposals are being developed for technical standards under which new tape drives will use explicit addressing. With explicit addressing, the host application or storage manager will issue tape access and positioning commands that specify the desired address. The following is an example of a series of explicit addressing commands that would carry out the same write sequence as the implicit write commands shown above: WRITE ADDRESS 0 LENGTH 2, WRITE ADDRESS 2 LENGTH 2, WRITE ADDRESS 4 LENGTH 2. Although explicit addressing will not offer random access, it will offer the advantage of making it easier to keep track of the location on tape that is being written. Explicit addressing will help avoid the situation where, as with implicit addressing, an inadvertent error in tracking the current tape location causes the storage subsystem to become confused as to where data is actually being written.

Although the explicit addressing tape drives are expected to constitute a significant advance, engineers at International Business Machines Corp. ("IBM") are still researching different tape storage approaches to even better serve their customers. In this respect, IBM engineers have recognized that one byproduct of the evolution toward explicit addressing might be the abandonment of costly and otherwise useful implicit addressing drives. Host applications and intermediate storage systems designed to operate with explicit addressing tape drives are not compatible with the "legacy" implicit addressing tape drives. In some cases,

customers may wish to purchase the latest storage subsystem but not abandon their legacy implicit addressing tape drives. For these customers, then, the state of the art is not completely adequate due to certain unsolved problems.

## SUMMARY OF THE INVENTION

5           Broadly, the present invention concerns the modification of an implicit addressing sequential media device by adding a hardware and/or software converter in order to simulate performance of an explicit addressing sequential media device from the perspective of host applications. Responsive to receiving explicit addressing read/write commands from the host application, the converter translates the explicit addressing read/write commands into implicit addressing read/write commands and passes the implicit addressing read/write commands through to the sequential media device. Optionally, responsive to drive capability queries from a host application, the converter reports that the drive utilizes explicit addressing. As another option, responsive to receiving commands other than explicit addressing read/write commands from the application host, the converter examines the commands to monitor sequential media position, and relays the commands to the drive substantially free of any modification.

15           The foregoing features may be implemented in a number of different forms. For example, the invention may be implemented to provide a method to interface an implicit addressing sequential media device with host applications designed for explicit addressing sequential media devices. In another embodiment, the invention may be implemented to provide an apparatus such as a storage system interface incorporating a converter with such functionality, or such a converter alone. In still another embodiment, the invention may be

20

implemented to provide a signal-bearing medium tangibly embodying a program of machine-readable instructions executable by a digital data processing apparatus to achieve the converter described herein. Another embodiment concerns logic circuitry having multiple interconnected electrically conductive elements configured to provide the converter explained herein.

The invention affords its users with a number of distinct advantages. Chiefly, the invention enables people to continue to use their implicit addressing sequential media drives (or other devices) with storage subsystems that are designed to operate with explicit addressing sequential media drives. Otherwise, these legacy drives would become out of date. This avoids the significant investment that would otherwise be required to purchase explicit addressing sequential media drives. Furthermore, the invention helps preserve the market for implicit address media drives because customers need not fear that their drives will rapidly go out of date. This is because the invention's converter insulates the legacy sequential media drives from changes in format, standards, and other technological changes occurring to the storage subsystem.

As another advantage, this invention allows implicit addressing drives to benefit from new tape features most easily enabled by an explicit addressing command set. An example of this is command queuing, in which incoming commands are collected and processed from a queue. This avoids having to reject earlier-arriving commands that seek to write to later addresses on tape, because they would otherwise create a gap in data. Command queuing provides a particular advantage when there is a long distance between the hosts and the sequential media devices. The invention also provides a number of other advantages and

benefits, which should be apparent from the following description of the invention.

## BRIEF DESCRIPTION OF THE DRAWINGS

FIGURE 1 is a block diagram of the hardware components and interconnections of a sequential media storage system according to the invention.

5 FIGURE 2 is a block diagram of a digital data processing machine according to the invention.

FIGURE 3 shows an exemplary signal-bearing medium according to the invention.

FIGURE 4 is a flowchart of an operational sequence for interfacing an implicit addressing sequential media device with host applications using explicit addressing, according to the invention.

## DETAILED DESCRIPTION

The nature, objectives, and advantages of the invention will become more apparent to those skilled in the art after considering the following detailed description in connection with the accompanying drawings.

## HARDWARE COMPONENTS & INTERCONNECTIONS

### 15 Overall Structure

FIGURE 1 shows an operating environment 100 to illustrate one exemplary implementation of the invention for purposes of explanation. Ordinarily skilled artisans will recognize that the invention may be implemented with various software, hardware, and architecture that varies from the illustrated example. The environment 100 includes at least one

of each of the following: host application 102, device driver 104, network 106, converter 108, and sequential media device 110. In one embodiment, the sequential media devices 110 comprise one or more sequential media drives such as tape drives.

### Host

5           The host application 102 comprises a physical host machine, software program, network, operator terminal, storage subsystem, hierarchical storage manager, user application program, or other source of various storage instructions directed at the sequential media device 110. Some examples of these instructions include Read commands, Write commands, Reposition commands, etc. The host application 102 provides data to be written by the device 110, receives data read by the devices 110, and communicates with the device 110 as needed to sustain workability.

### Device Driver

15           The device driver 104 is a software component that brokers between the host application 102 and the media devices 110. The device driver 104 frees the host application 102 from various details about the operation of the network 106. The device driver 104 may be part of an operating system at the host 102, a product associated with the network 106, the application 102, or a product from a gateway vendor, for example. Still, the invention may operate without the device driver 104, and this component is therefore optional. One example of the device driver 104 is an AIX operating system component (102) that is provided with purchase of an  
20           IBM machine type 3590 tape drive (110).

## Network

Depending upon the desired storage configuration, the optional network 106 may be used or omitted. Some useful examples of the network 106 include a storage area network, or another arrangement of switches, routers, and/or gateways. Some other examples include a local area network (LAN), wide area network (WAN), token ring, or other communications link. Still another example is a simpler product such as a media controller card.

## Converter

The converter 108 is a new component added to the environment 100 in order to implement the functionality of the present invention. The converter may comprise, for example, a router/gateway or another known construct utilized to convert between different protocols. For example, the converter 108 may convert between iSCSI or SCSI protocol from the network 106 and Fibre Channel protocol at the device 110. One particular example of the converter 108 is the IBM machine type 2108 model G07 product. In the typical implementation, a router/gateway only manipulates the carrier wrapper, that is, the format of commands passing through the router/gateway. As discussed in greater detail below, the converter 108 additionally changes the contents of commands passing through it. Namely, the addressing scheme is changed. More particularly, the converter 108 mimics performance of an explicit addressing sequential media drive from the perspective of the host application 102, even though the device 110 actually utilizes implicit addressing. The converter 108 also translates explicit addressing



commands from the host application 102 into implicit addressing commands compatible with the device 110.

FIGURE 1 shows one example of the converter 108, although many different arrangements are possible. The converter 108 includes an input port 108a, output port 108c, and a processor 108b. The processor 108b tracks the current tape position (address) using the current media position record 108d. Namely, the converter 108 includes a record 108d of the current media position, in order to ease the implementation of explicit addressing commands on the implicit addressing device 110. In one example, the current media position comprises the relative position between a tape read/write head and the magnetic tape media. The record 108a may comprise a register, byte, page, firmware location, software construct, hardware site, or other means to keep track of the address or other current logical write position of the sequential media device 110.

The ports 108a, 108c may comprise connectors, busses, intelligent communications devices, channels, optical links, wireless links, planar connections, host bus adapters, gigabit interface connectors (GBICs), or any other construct as appropriate to the application at hand. For example, the ports 108a, 108c may comprise circuit elements to implement low level device drivers, etc. The processor 108b comprises a digital data processor, which may be implemented in various ways, as discussed below. As an alternative to the previously described embodiment of converter 108, this component may also be implemented as a software component of a host 102, network 106, or device 110.

In one embodiment, as discussed above, there is a single instance of the converter 108. In another embodiment, the system 100 includes multiple converters 108 between the host

application 102 and sequential media devices 110. The converters 108 may use separate device drivers 104 and networks 106, or some or all of these components may be shared among converters 108. Where multiple converters 108 are utilized, the converters are suitably coupled to exchange information sufficient for all converters to monitor current media position of the device 110.

### Sequential Media Device

In one embodiment, the sequential media device 110 comprises one or more drives to access removable, sequentially accessible media such as magnetic tape, optical tape, etc. For ease of illustration, the present discussion utilizes magnetic tape. In this context, one example of device 110 is an IBM machine type 3590 product. Such a drive may include one tape drive, as discussed, or an arrangement of multiple drives. In an alternative embodiment, the sequential media devices comprise virtual sequential media drives rather than physical tape drives. Such a virtual device may comprise, for example, a storage manager, controller, interface, or other processing component that conducts communications as if it were a sequential media drive, yet implements received storage instructions on DASD or other non-sequential media, or forwards such instructions to a non-sequential storage controller to be implemented therein. In this sense, sequential media "devices" as discussed herein may comprise actual or virtual sequential media storage machines.

### Exemplary Digital Data Processing Apparatus

As mentioned above, the converter 108 may be implemented in various forms. As one example, the converter 108 may comprise a digital data processing apparatus, as exemplified by the hardware components and interconnections of the digital data processing apparatus 200 of FIGURE 2.

5 The apparatus 200 includes a processor 202, such as a microprocessor, personal computer, workstation, or other processing machine, coupled to a storage 204. In the present example, the storage 204 includes a fast-access storage 206, as well as nonvolatile storage 208. The fast-access storage 206 may comprise random access memory ("RAM"), and may be used to store the programming instructions executed by the processor 202. The nonvolatile storage 208 may comprise, for example, battery backup RAM, EEPROM, one or more magnetic data storage disks such as a "hard drive", a tape drive, or any other suitable storage device. The apparatus 200 also includes an input/output 210, such as a line, bus, cable, electromagnetic link, or other means for the processor 202 to exchange data with other hardware external to the apparatus 200.

10 Despite the specific foregoing description, ordinarily skilled artisans (having the benefit of this disclosure) will recognize that the apparatus discussed above may be implemented in a machine of different construction, without departing from the scope of the invention. As a specific example, one of the components 206, 208 may be eliminated; furthermore, the storage 204, 206, and/or 208 may be provided on-board the processor 202, or even provided externally to the apparatus 200.

#### Logic Circuitry

5 In contrast to the digital data processing apparatus discussed above, a different embodiment of the invention uses logic circuitry instead of computer-executed instructions to implement the converter 108. Depending upon the particular requirements of the application in the areas of speed, expense, tooling costs, and the like, this logic may be implemented by constructing an application-specific integrated circuit ("ASIC") having thousands of tiny integrated transistors. Such an ASIC may be implemented with CMOS, TTL, VLSI, or another suitable construction. Other alternatives include a digital signal processing chip ("DSP"), discrete circuitry (such as resistors, capacitors, diodes, inductors, and transistors), field programmable gate array ("FPGA"), programmable logic array ("PLA"), and the like.

## 10 OPERATION

Having described the structural features of the present invention, the operational aspect of the present invention will now be described. As mentioned above, the operational aspect of the invention generally involves modifying an implicit addressing sequential media drive by adding a hardware and/or software converter in order to simulate performance of an explicit addressing sequential media drive from the perspective of host applications.

### 15 Signal-Bearing Media

20 Wherever the functionality of the invention is implemented using machine-executed program sequences, these sequences may be embodied in various forms of signal-bearing media. In the context of FIGURE 2, this signal-bearing media may comprise, for example, the storage 204 or another signal-bearing media, such as a magnetic data storage diskette 300

(FIGURE 3), directly or indirectly accessible by a processor 202. Whether contained in the storage 206, diskette 300, or elsewhere, the instructions may be stored on a variety of machine-readable data storage media. Some examples include direct access storage (e.g., a conventional "hard drive", redundant array of inexpensive disks ("RAID"), or another direct access storage device ("DASD")), serial-access storage such as magnetic or optical tape, electronic non-volatile memory (e.g., ROM, EPROM, or EEPROM), battery backup RAM, optical storage (e.g., CD-ROM, WORM, DVD), paper "punch" cards, or other suitable signal-bearing media including analog or digital transmission media and analog and communication links and wireless communications. In an illustrative embodiment of the invention, the machine-readable instructions may comprise software object code assembled from assembly language, compiled from a language such as "C," etc.

#### Logic Circuitry

In contrast to the signal-bearing medium discussed above, some or all of the invention's functionality may be implemented using logic circuitry, instead of using a processor to execute instructions. Such logic circuitry is therefore configured to perform operations to carry out the method of the invention. The logic circuitry may be implemented using many different types of circuitry, as discussed above.

#### Overall Sequence of Operation

FIGURE 4 shows a sequence 400 to illustrate one example of the method aspect of the present invention. For ease of explanation, but without any intended limitation, the example of

FIGURE 4 is described in the context of the storage environment 100 described above. Also for ease of discussion, the present illustration concerns an embodiment utilizing a single, physical tape drive as the device 110. The sequence 400 is initiated in step 402, when technicians install the device driver 104, network 106, and converter 108. Installation entails electrically coupling the network 106 between the machine(s) running the host application 102 and the converter 108, and coupling the converter 108 to the drive 110. In cases where the converter 108 is integrated into the network 106, the network 106 is coupled directly to the drives 110. Configuration of the network 106 entails installing and/or activating the device driver 104 and any necessary software configuration steps to prepare the driver 104, network 106, and converter 108 for operation, some or all of which may be known to those skilled in the art. Also as part of step 402, the converter 108 conducts a survey to identify the number, type, and other properties of the attached drives 110. When step 402 completes, operation of the converter 108 begin (step 403).

Steps 404, 406 describe the events that occur when the converter 108 receives and then processes a command from the host application 102 relayed by the network 106. In step 404, the converter 108 receives a host application command. "Commands" comprise instructions for the drive 110 to report its capability, conduct a read and/or write operation ("read/write operation"), reposition the tape, allow changes to its operating mode, report status, and the like. The drive 110 may recognize other commands as well.

In one case (step 404a), the converter 108 in step 404 receives a query command requesting a report of the drive's capability, properties, type, model, etc. In this case, the

converter 108 conditions the drive's response to assert that the drive utilizes explicit addressing (step 406a).

5 In another case (step 404b), the converter 108 in step 404 receives an explicit addressing read/write command (also called a media access command). In this case, the converter 108 proceeds to confirm the command's validity against predetermined syntax rules, etc. (step 406b). Step 406b may also impose other requirements, such as requiring that any write command is not valid unless it is directed to the beginning of tape or current tape position (unless it directs a full re-write of the most recently written data). The reason for these requirements is because most tape technologies are absolutely sequential in their ability to write data and the misordering of a write operation cannot always be easily repaired.

10 If the command is valid, the converter 108 converts the explicit addressing read/write command into an appropriate implicit read/write command (step 406c). Explicit addressing read/write commands include a command (such as Read or Write), an address to perform the read/write, and a length of data to be written/read. Conversion requires generation of the following resultant commands:

- 20 1. POSITIONING COMMAND (as required). Positioning commands work to change the relative position between the tape and the drive's read/write head, thereby changing the current logical block number being accessed by the drive 110. Positioning commands may be needed, for example, when the sequential media device's current position (e.g., logical block number) does not match the explicit address of the explicit logical block address command. Some other examples where repositioning may be needed include repositioning over previously written

file or other end marks to start writing (appending) new data, performing a write retry after a timeout or error, writing over old data to be discarded, etc. In one embodiment, positioning may be achieved by performing a LOCATE command with the appropriate block number to reposition the tape drive before issuing the converted command.

2. IMPLICIT ADDRESS COMMAND. The implicit address command is generated by removing the address from the explicit address command and retaining the command and data length.
3. READ POSITION COMMAND (as required). The Read Position command is needed if the explicit addressing command is a relative command or another reason makes it difficult to determine current tape position. For instance, a Read Position command may be used whenever the tape drive 110 reports any Check Condition error.

The following example provides a specific example of the explicit addressing command conversion of step 406c. Upon receiving the commands WRITE ADDRESS 4 LENGTH 10, WRITE ADDRESS 0 LENGTH 1, WRITE ADDRESS 1 LENGTH 3, the converter implements them as the following commands, in order: WRITE LENGTH 1, WRITE LENGTH 3, WRITE LENGTH 10.

After the conversion, the converter 108 passes the converted, now-implicit-addressing command to the drive 110. If the command is a Write command, the converter 108 also updates the record of current media position 108d to show the tape drive's current address, relative head position, or other indication of logical write position.



1  
2  
3  
4  
5  
6  
7  
8  
9  
10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000

In an optional enhancement to the invention, the converter 108 may perform command queuing to avoid having to reject earlier-arriving commands that seek to write to later addresses on tape (because they would otherwise create a gap in data). In this embodiment, the converter 108 accumulates a number of arriving explicit addressing commands and re-orders them according to their stated addresses before the conversion of step 404c. Alternatively, the converter 108 may convert the commands to implicit addressing first, then re-order them according to their formerly stated explicit address. The converter 108 may accumulate commands to the limit of a buffer, or to the limits of a desired maximum send-to-write delay time, or another criteria. Later arriving commands that seek to write to sequential media addresses earlier than the current address may be rejected, for example, by the converter 108 returning an error message to the host application 102. As an optional enhancement to step 406c, if the converter 108 determines that the current command is a retry of a prior successful Write command, the converter 108 may discard the command and provide a status report of "good" back to the host application 102.

In contrast to steps 404a, 404b, another possibility is that the converter 108 receives a command other than an explicit addressing read/write command (step 404c). For instance, the command of step 404 may be an implicit read/write command, a repositioning command, etc. In this case, the converter 108 reviews the contents of the command to monitor the current tape position, updates the record 108d, and then passes the command to the drive 110 (step 406d). For example, if the command is an implicit write command that advances the tape by two logical blocks, then the converter 108 advances the current media position record 108a by two blocks. "Relative" commands such as Space and Reposition, however, are not self-

descriptive in the amount that they change tape position. More particularly, a reposition command endeavors to reposition the tape to the next file marker. In such cases, step 406d involves the converter 108 passing the command on to the drive 110, waiting until the drive 110 completes the command, querying the drive 110 for the current tape address (or other logical position), then updating the record 108d. This query may be done by issuing a Read Position command, for instance. It may also be necessary to query the drive, for example, when Unit Attention conditions imply that a logical block address has changed. The reported current tape position is then used to update the record 108a.

#### OTHER EMBODIMENTS

While the foregoing disclosure shows a number of illustrative embodiments of the invention, it will be apparent to those skilled in the art that various changes and modifications can be made herein without departing from the scope of the invention as defined by the appended claims. Furthermore, although elements of the invention may be described or claimed in the singular, the plural is contemplated unless limitation to the singular is explicitly stated. Additionally, ordinarily skilled artisans will recognize that operational sequences must be set forth in some specific order for the purpose of explanation and claiming, but the present invention contemplates various changes beyond such specific order.